

**$N(1880) 1/2^+$**

$$I(J^P) = \frac{1}{2}(\frac{1}{2}^+) \text{ Status: } **$$

OMITTED FROM SUMMARY TABLE

**$N(1880)$  BREIT-WIGNER MASS**

<u>VALUE (MeV)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
1870 ± 35	ANISOVICH 12A	DPWA	Multichannel
● ● ● We do not use the following data for averages, fits, limits, etc. ● ● ●			
1900 ± 36	SHRESTHA 12A	DPWA	Multichannel
1885 ± 30	MANLEY 92	IPWA	$\pi N \rightarrow \pi N$ & $N\pi\pi$

**$N(1880)$  BREIT-WIGNER WIDTH**

<u>VALUE (MeV)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
235 ± 65	ANISOVICH 12A	DPWA	Multichannel
● ● ● We do not use the following data for averages, fits, limits, etc. ● ● ●			
485 ± 142	SHRESTHA 12A	DPWA	Multichannel
113 ± 44	MANLEY 92	IPWA	$\pi N \rightarrow \pi N$ & $N\pi\pi$

**$N(1880)$  POLE POSITION**

**REAL PART**

<u>VALUE (MeV)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
1860 ± 35	ANISOVICH 12A	DPWA	Multichannel
● ● ● We do not use the following data for averages, fits, limits, etc. ● ● ●			
1801	SHRESTHA 12A	DPWA	Multichannel

**−2×IMAGINARY PART**

<u>VALUE (MeV)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
250 ± 70	ANISOVICH 12A	DPWA	Multichannel
● ● ● We do not use the following data for averages, fits, limits, etc. ● ● ●			
383	SHRESTHA 12A	DPWA	Multichannel

**$N(1880)$  ELASTIC POLE RESIDUE**

**MODULUS  $|r|$**

<u>VALUE (MeV)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
6 ± 4	ANISOVICH 12A	DPWA	Multichannel

**PHASE  $\theta$**

<u>VALUE (°)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
80 ± 65	ANISOVICH 12A	DPWA	Multichannel

## N(1880) INELASTIC POLE RESIDUE

The “normalized residue” is the residue divided by  $\Gamma_{pole}/2$ .

### Normalized residue in $N\pi \rightarrow N(1880) \rightarrow N\eta$

<u>MODULUS (%)</u>	<u>PHASE (°)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
11 ± 7	−75 ± 55	ANISOVICH	12A DPWA	Multichannel

### Normalized residue in $N\pi \rightarrow N(1880) \rightarrow \Lambda K$

<u>MODULUS (%)</u>	<u>PHASE (°)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
3 ± 2	40 ± 40	ANISOVICH	12A DPWA	Multichannel

### Normalized residue in $N\pi \rightarrow N(1880) \rightarrow \Sigma K$

<u>MODULUS (%)</u>	<u>PHASE (°)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
11 ± 6	95 ± 40	ANISOVICH	12A DPWA	Multichannel

### Normalized residue in $N\pi \rightarrow N(1880) \rightarrow \Delta\pi, P\text{-wave}$

<u>MODULUS (%)</u>	<u>PHASE (°)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
20 ± 8	−150 ± 50	ANISOVICH	12A DPWA	Multichannel

## N(1880) DECAY MODES

Mode
$\Gamma_1$ $N\pi$
$\Gamma_2$ $N\eta$
$\Gamma_3$ $\Lambda K$
$\Gamma_4$ $\Sigma K$
$\Gamma_5$ $\Delta(1232)\pi$
$\Gamma_6$ $N\rho, S=1/2$
$\Gamma_7$ $N(\pi\pi)_{S=0}^{I=0}$ $S\text{-wave}$
$\Gamma_8$ $p\gamma$
$\Gamma_9$ $n\gamma$

## N(1880) BRANCHING RATIOS

$\Gamma(N\pi)/\Gamma_{total}$	$\Gamma_1/\Gamma$		
<u>VALUE (%)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
5 ± 3	ANISOVICH	12A DPWA	Multichannel
● ● ● We do not use the following data for averages, fits, limits, etc. ● ● ●			
15 ± 5	SHRESTHA	12A DPWA	Multichannel
15 ± 6	MANLEY	92 IPWA	$\pi N \rightarrow \pi N$ & $N\pi\pi$

$\Gamma(N\eta)/\Gamma_{total}$	$\Gamma_2/\Gamma$		
<u>VALUE (%)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
25 <sup>+30</sup> <sub>−20</sub>	ANISOVICH	12A DPWA	Multichannel
● ● ● We do not use the following data for averages, fits, limits, etc. ● ● ●			
16 ± 7	SHRESTHA	12A DPWA	Multichannel

**$\Gamma(\Lambda K)/\Gamma_{\text{total}}$   $\Gamma_3/\Gamma$**

<u>VALUE (%)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
$2 \pm 1$	ANISOVICH 12A	DPWA	Multichannel
• • • We do not use the following data for averages, fits, limits, etc. • • •			
$32 \pm 10$	SHRESTHA 12A	DPWA	Multichannel

**$\Gamma(\Sigma K)/\Gamma_{\text{total}}$   $\Gamma_4/\Gamma$**

<u>VALUE (%)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
$17 \pm 7$	ANISOVICH 12A	DPWA	Multichannel

**$\Gamma(\Delta(1232)\pi)/\Gamma_{\text{total}}$   $\Gamma_5/\Gamma$**

<u>VALUE (%)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
$29 \pm 12$	ANISOVICH 12A	DPWA	Multichannel
• • • We do not use the following data for averages, fits, limits, etc. • • •			
$< 2$	SHRESTHA 12A	DPWA	Multichannel

**$\Gamma(N\rho, S=1/2)/\Gamma_{\text{total}}$   $\Gamma_6/\Gamma$**

<u>VALUE (%)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
• • • We do not use the following data for averages, fits, limits, etc. • • •			
$< 1$	SHRESTHA 12A	DPWA	Multichannel

**$\Gamma(N(\pi\pi)_{S=0}^{I=0})/\Gamma_{\text{total}}$   $\Gamma_7/\Gamma$**

<u>VALUE (%)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
• • • We do not use the following data for averages, fits, limits, etc. • • •			
$8 \pm 5$	SHRESTHA 12A	DPWA	Multichannel

**$N(1880)$  PHOTON DECAY AMPLITUDES**

**$N(1880) \rightarrow \rho\gamma$ , helicity-1/2 amplitude  $A_{1/2}$**

<u>VALUE (<math>\text{GeV}^{-1/2}</math>)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
$0.014 \pm 0.003$	<sup>1</sup> ANISOVICH 12A	DPWA	Phase = $(-130 \pm 60)^\circ$
• • • We do not use the following data for averages, fits, limits, etc. • • •			
$0.021 \pm 0.006$	SHRESTHA 12A	DPWA	Multichannel

**$N(1880) \rightarrow n\gamma$ , helicity-1/2 amplitude  $A_{1/2}$**

<u>VALUE (<math>\text{GeV}^{-1/2}</math>)</u>	<u>DOCUMENT ID</u>	<u>TECN</u>	<u>COMMENT</u>
• • • We do not use the following data for averages, fits, limits, etc. • • •			
$0.014 \pm 0.007$	SHRESTHA 12A	DPWA	Multichannel

**$N(1880)$  FOOTNOTES**

<sup>1</sup> This ANISOVICH 12A value is the complex helicity amplitude at the pole position.

**$N(1880)$  REFERENCES**

ANISOVICH 12A	EPJ A48 15	A.V. Anisovich <i>et al.</i>	(BONN, PNPI)
SHRESTHA 12A	PR C86 055203	M. Shrestha, D.M. Manley	(KSU)
MANLEY 92	PR D45 4002	D.M. Manley, E.M. Saleski	(KSA)
Also	PR D30 904	D.M. Manley <i>et al.</i>	(VPI)